

# 0.3A, 30V Schottky Barrier Diodes

#### **Features**

- AEC-Q101 Qualified
- Halogen and Antimony Free(HAF), RoHS compliant






**SOT-23** 

### **Mechanical Data**

- SOT-23 Small Outline Plastic Package
- Epoxy UL: 94V-0

#### **Epuivalent circuit**



Absolute Maximum Ratings (T <sub>a</sub> =25°C unless otherwise noted)						
Parameters	Symbol	Value	Unit			
Repetitive Peak Reverse Voltage	V <sub>RRM</sub>	30	V			
Average Rectified Forward Current	I <sub>F(AV)</sub>	300	mA			
Repetitive Peak Forward Current	I <sub>FRM</sub>	350	mA			
Non-Repetitive Peak Forward Surge Current at Pulse width = 1 second	IFSM	600	mA			
Power Dissipation	P <sub>D</sub>	290	mW			
Operating Junction Temperature Range	Tj	- 55 to + 150	°C			
Storage Temperature Range	T <sub>stg</sub>	- 55 to + 150	°C			

Thermal Characteristics			
Parameter	Symbol	Value	Unit
Typical Thermal Resistance Junction-to-Ambient (Note 1)	R <sub>θ</sub> JA	430	°C/W

Note 1: Device mounted on FR-4 substrate PC board, 2oz copper, with minimum recommended pad layout.



# ABAT54-A-C-S GOOD-ARK Electronics

Electrical Characteristics (Ta = 25°C unless otherwise noted)						
Parameter Syr		Test Conditions	Min.	Max.	Unit	
Reverse Breakdown Voltage	$V_{(BR)R}$	I <sub>R</sub> =10µA	30	-	V	
		I <sub>F</sub> =0.1mA	-	240		
		I <sub>F</sub> =1mA	-	320		
Forward Voltage	VF	I <sub>F</sub> =10mA	- 400		mV	
		I <sub>F</sub> =30mA	-	500		
		IF =100mA	-	800		
Reverse Current	I <sub>R</sub>	V <sub>R</sub> =25V	-	2	μA	
Reverse Recovery Time	t <sub>rr</sub>	From I <sub>F</sub> = 10 mA through I <sub>R</sub> = 10 mA to I <sub>RR</sub> = 1 mA , RL = 100 $\Omega$	-	5	ns	
Total Capacitance	C <sub>tot</sub>	$V_R = 1 V, f = 1MHz$	-	10	pF	



## **Typical Characteristics Curves**




Fig 1. Reverse Characteristics Curve




Fig 2. Forward Characteristics Curve




Fig 3. Junction Capacitance






Fig 4. Average Rectified Current Derating Curve




### Package Outline Dimensions (Unit: millimeters)

**SOT-23** 








Unit	А	A1	В	С	D	Е	F	G	L	L1
mm	1.20	0.100	1.40	0.19	3.04	2.6	1.02	2.04	0.51	0.2
	0.89	0.013	1.20	0.08	2.80	2.2	0.89	1.78	0.37	MIN


# Recommended Soldering Footprint (Unit: millimeters)



### **Packing Information**

Package	Tape Width	Pitch		Reel	Size	Per Reel Packing	
SOT-23	mm	mm	inch	mm	inch	Quantity	
301-23	8	4±0.1	0.157±0.004	178	7	3000	

# **Marking Information**



Font type: Arial

Туре	Marking	Туре	Marking	Туре	Marking	Туре	Marking
ABAT54	L4	ABAT54A	L42	ABAT54C	L43	ABAT54S	L44

### **Revision History**

Version	Date	Description of changes
Rev.A	2025.10.16	Primary



# ABAT54-A-C-S GOOD-ARK Electronics

#### **Disclaimers**

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.